

# marantz®



## MODEL 30

### Marantz MODEL 30 Integrated Amplifier

Get the most musical sound possible from this beautiful, integrated amplifier. Exquisitely tuned by the Marantz Sound Master, the MODEL 30 integrated amplifier features a master-curated Marantz HDAM and a fully discrete design for luxurious Hi-Fi purity. Designed to last the test of time and make all your music unforgettable.

- Custom-built preamplifier with Marantz HDAM technology.
- Tuned with passion by the Marantz Sound Master.
- Output: 100W + 100W (8ohm), 200W + 200W (4ohm).
- Fully-discrete design for signal purity.
- Custom HDAM®-SA3 circuitry for clean, optimal dynamics.
- Separate amp and preamp power supplies reduce interference.
- Toroidal transformer dedicated to preamp for clarity and power.
- Current feedback preamp design with its wide-range circuitry.
- MM/MC Phono input with its Premium Phono EQ circuit.
- Brass machined input terminals for CD and Phono.
- Marantz original high-quality/high-purity copper speaker terminals.
- Linear volume control with new electric volume system.
- Amplifier design inherited from our flagship models.
- Available in Black and Silver Gold.



## Modern Musical Luxury



# MODEL 30

## Technical Specifications



<b>Output Power</b>	
Rated Output Power	100W + 100W (8ohm) 200W + 200W (4ohm)
<b>Features</b>	
Amplifier Circuit	Switching Amplifier
Power Transformer	Toroidal w/ case
Volume	Electric
Bass / Treble / Mid / Balance Control	yes / yes / - / yes
Source Direct	yes
Wide Range	5Hz - 50kHz
Total Harmonic distortion	0.005% (1kHz, 8Ω)
Dumping Factor	500
Input Sensitivity: Phono input	MM: 2.3 mV / 39 kohm MC: 250 μV / 100 ohm
Input Sensitivity: CD/LINE/RECORDER	220 mV / 13 kohm
Input Sensitivity: Power Amplifier input	1.1 V / 13 kohm
SN Ratio	PHONO (MM): 88dB PHONO (MC): 75dB CD: 107dB
<b>Terminal</b>	
Phono Input	yes (MM/MC) Marantz Musical Premium Phono EQ
Ext. Pre Input (Power Amp Direct)	yes
Preout	yes
Audio (In/Out) Terminals	6/1 (PHONO / MM&MC / CD / TUNER / LINE 1 / LINE 2 / RECORDER) * [PHONO] and [CD] inputs = high grade terminals
Speaker Terminal	Marantz Original SPKT-100+
Remote Control Bus Terminal	yes (Cinch)
<b>UI</b>	
Display	yes (Porthole, OLED)
<b>Control</b>	
App Control via Network Player	yes
System Remote Controller	yes (New system remote controller to control SACD 30 and MODEL 30)

<b>Other</b>			
Unit (W x H x D mm)	443 x 130 x 432		
Packaging Dimensions (W x H x D mm)	534 x 255 x 522		
Net weight	14.8kg		
Packaging gross weight	17.6kg		
Unit (W x H x D in inches)	17.4" x 5.1" x 1.7"		
Packaging Dimensions (W x H x D in inches)	20" x 10.1" x 20.6"		
Weight	32 lbs 3 Oz		
Packaging Weight	37 lbs 8 Oz		
Power Consumption	130W at Standby 0.2W		
AC Inlet	yes		
Quick Start Guide	Paper		
<b>Cosmetic</b>			
Panel Color	SG / BK		
Front Center Panel	Aluminum		
Side cover	Aluminum		
Top cover	Steel		
Edge-lighting	yes (Dimmer)		
Volume Knob	Aluminum		
Input Selector	Aluminum		
Bass/Treble/Balance/ REC Out Sel knobs	REC Out-->PHONO (Aluminum)		
Power button	Aluminum		
Side screw	Copper plated		
Chassis Material	SECC		
Chassis Layer	Triple		
Foot	New (PM6006 type)		
<b>UPC</b>			
USA	MODEL30/U1B	699927170059	Black
USA	MODEL30/U1SG	699927170158	Silver Gold

Design and specifications are subject to change by Marantz without notice

[www.ValueElectronics.com](http://www.ValueElectronics.com)

